


TECHNICAL SPECIFICATIONS

FTP-14A

BIAS TAP



The FTP-14A Bias Tap is used to provide a DC path to one side of a 50 Ohm transmission line. An integral blocking capacitor isolates the DC from the other side of the line.

Frequency Range	50 - 512 MHz
Insertion Loss	0.2 dB maximum
VSWR	1.3:1 maximum
DC Resistance	1 Ohm maximum
DC Voltage	200 Volts maximum
DC Current	700 mA maximum

OPTION: FTP-14AR - Provides DC path to the N-female connector.

METROPOLE PRODUCTS, INC.

Rev. 7/06

Metropole Products, Inc., P.O. Box 309, Stafford, Virginia 22555
540-659-2132/Voice 540-659-2133/Fax