

**MPI**

# TECHNICAL SPECIFICATIONS

**FBV-6C-3600  
BANDPASS FILTER**

**HIGH PERFORMANCE  
COMPACT SIZE**

## ELECTRICAL SPECIFICATIONS

Center Frequency:	3600 MHz
Insertion Loss:	1.0 dB max.
1 dB Bandwidth	200 MHz
Rejection:	
0 to 3.28 GHz	80 dB min.
3.28 to 3.36 GHz	50 dB min.
3.86 to 3.95 GHz	50 dB min.
3.95 to 11.3 GHz	80 dB min.
Impedance, nominal	50 Ohms
Connectors:	SMA-female
Size:	5.50" long x .75" wide x .75" high
Weight:	5 oz.

**METROPOLE PRODUCTS, INC.**

Metropole Products, Inc., P.O. Box 309, Stafford, Virginia 22555  
540-659-2132/Voice 540-659-2133/Fax

Rev. 12/2005